

Purpose:

This note documents the command line switches available for the ScadaPhone program.

Applies To:

All versions from Version 4.2 up.

Note:

1. To have ScadaPhone load a specific project at startup:

/PROJECT:<project-dir>

If <project-dir> contains a space, bracket the path with double quotes.

examples:

C:\ScadaTEC\ScadaPhone.exe /PROJECT:C:\Temp

C:\ScadaTEC\ScadaPhone.exe /PROJECT:"C:\My Documents\Temp"

2. To force ScadaPhone to start up in a specific mode:

/MODE:<RUN/DEVELOPMENT>

examples:

C:\ScadaTEC\ScadaPhone.exe /MODE:DEVELOPMENT

C:\ScadaTEC\ScadaPhone.exe /MODE:RUN

3. If either /PROJECT: or /MODE: are not specified, the value from the INI file is used and ScadaPhone will start up in the same mode it was shut down in..

4. To bypass the log-in security system and eliminate the need to log in.:

/NOSECURITY

example:

C:\ScadaTEC\ScadaPhone.exe /NOSECURITY

5. To display Scadasis in the list of OLE servers:

/OLE

example:

C:\ScadaTEC\ScadaPhone.exe /OLE

6. To allow multiple copies of ScadaPhone to run simultaneously:

/MULTINS

example:

C:\ScadaTEC\ScadaPhone.exe /MULTINS